

THE COMMISSIONER OF PATENTS AND TRADEMARKS  
Washington D.C. 20231  
Box Patent Applications

Case Docket No. FUIJX 17.182  
Filed by Express Mail  
(Receipt No. EL522391580US)  
on March 29, 2000  
pursuant to 37 CFR 1.110  
by Lydia Gonzalez

S I R:

Transmitted herewith for filing is: ☒ a new application  
☐ a c-i-p application of S.N. \_\_\_\_\_ filed \_\_\_\_\_

Inventor(s): Masatsugu FUJII

For: CODING ASSISTING EQUIPMENT, DECODING ASSISTING EQUIPMENT,  
RADIO TRANSMITTER, AND RADIO RECEIVER

Enclosed are:

- ☒ 11 sheets of drawings (Figs. 1-11)  
☒ Specification, including claims ad abstract ( 40 pages)  
☒ Declaration  
☒ An assignment of the Invention to FUJITSU LIMITED  
☒ A certified copy of Japanese Application No(s). 11-215290  
☐ An associate power of attorney  
☐ A verified statement to establish small entity status under 37 CFR 1.9 and 37 CFR 1.27  
☒ Post card  
☒ Recording fee (as indicated below)  
☒ Information Disclosure Statement, PTO-1449, copies of 4 references  
☐ Other \_\_\_\_\_  
☐ Other \_\_\_\_\_

	Col. 1	Col. 2
FOR:	NO. FILED	NO. EXTRA
BASIC FEE		
TOTAL CLAIMS	16-20 =	0
INDEP CLAIMS	4-3 =	1
<input type="checkbox"/> MULTIPLE DEPENDENT CLAIMS PRESENTED		

\*If the difference in Col. 1 is less than zero, enter "0" in Col. 2

SMALL ENTITY	
RATE	FEE
	\$345
x 9 =	\$
x 39 =	\$
x 130 =	\$
TOTAL	\$

OTHER THAN A SMALL ENTITY	
RATE	FEE
	\$690
x 18 =	\$
x 78 =	\$ 78
x 260 =	\$
TOTAL	\$768

☐ Please charge our Deposit Account No. 08-1634 the amount of \_\_\_\_\_ to cover the filing fee and recording fee (if any)

☒ A check in the amount of \$808.00 to cover the filing fee and the recording fee (if any) is enclosed.


☒ The Commissioner is hereby authorized to charge payment of any fee associated with this communication or credit overpayment to Deposit Account No. 08-1634. A duplicate copy of this sheet is enclosed.

Helfgott & Karas, P.C.  
60<sup>th</sup> Floor  
Empire State Building  
New York, New York 10118-6098  
(212)643-5000

Date: March 29, 2000

Any fee due with this paper, not fully covered by an enclosed check, may be charged on Deposit Acct No. 08-1634

Respectfully Submitted,



- ☐ Aaron B. Karas, Reg. No. 18,923  
☒ Samson Helfgott, Reg. No. 23,072  
☐ Leonard Cooper, Reg. No. 27,625  
☐ Linda S. Chan, Reg. No. 42,400  
☐ Jacqueline M. Steady, Reg. No. 44,354  
☐ Harris A. Wolin, Reg. No. 39,432

U.S. PTO  
09/537786  
03/29/00

# **CODING ASSISTING EQUIPMENT, DECODING ASSISTING EQUIPMENT, RADIO TRANSMITTER, AND RADIO RECEIVER**

## **BACKGROUND OF THE INVENTION**

5

### **1. Field of the Invention**

The present invention relates to a coding assisting equipment and a decoding assisting equipment that are fed with information that is split into pieces having a predetermined word length and assist coding and decoding, respectively, of the information, as well as to the coding assisting equipment and the decoding assisting apparatus having such a coding assisting equipment or decoding assisting equipment.

### **2. Description of the Related Art**

15 In recent years, a variety of digital modulation systems have been applied to mobile communication systems and other radio transmission systems to effectively utilize radio frequencies and realize high transmission rates.

At transmitting ends and receiving ends of such mobile communication systems, to secure desired transmission quality even in a state that the transmission characteristics of a radio transmission channel formed between a mobile station and a radio base station severely degrades, coding/decoding, interleave processing, and other processing that are adapted to such a radio transmission channel are performed.

25 Fig. 10 shows an example configuration of a coding part that is incorporated in a mobile station equipment.

In Fig. 10, a first output port of a processor (not shown) is connected to the input of a transmitter buffer 121. The output of the transmitter buffer 121 is connected to a parallel load terminal of a shift register 122. A clock terminal CL of the shift register 122, a read control terminal C of the transmitter buffer 121, and the output and a clock input CL of a counter 123 are connected to the corresponding input/output terminals of a controlling part 124. A second output port of the processor is connected to a reset terminal of the counter 123 and an activation input of the controlling

30  
35

part 124. A serial output of the shift register 122 is connected to a corresponding input of a CRC operation part 125, and the output of the CRC operation part 125 is connected to a modulation input of a transmitting part (not shown) via a convolutional coding part 126 and an interleaver 127. Corresponding outputs of the controlling part 124 are connected to respective control inputs of the CRC operation part 125 and the convolutional coding part 126.

The CRC operation part 125 is composed of a selector 128 one input of which is directly connected to the serial output of the shift register 122 and that is disposed as the final stage, an exclusive-OR gate 129 one input of which is directly connected to the serial output of the shift register 122 together with the one input of the selector 128, flip-flops (FFs) 130-1 and 130-2 that are cascaded to the output of the exclusive-OR gate 129, an exclusive-OR gate 131 one input of which is connected to the output of the exclusive-OR gate 129 together with the input of the flip-flop 130-1 and the other input of which is connected to the output of the flip-flop 130-2, and a flip-flop (FF) 130-3 the input of which is connected to the output of the exclusive-OR gate 131 and the output of which is connected to the other inputs of the exclusive-OR gate 129 and the selector 128.

The convolutional coding part 126 is composed of a cascade connection of flip-flops (FFs) 131-1 to 131-3 that is connected to the output of the CRC operation part 125 (selector 128), an exclusive-OR gate 132-1 having two inputs that are directly connected to the outputs of the respective flip-flops 131-1 and 131-2, an exclusive-OR gate 132-2 having two inputs that are directly connected to the outputs of the respective flip-flops 131-1 and 131-3, and a selector 133 that is disposed as the final stage and has two inputs that are connected to the outputs of the respective exclusive-OR gates 132-1 and 132-2.

In the above-configured conventional example, transmission information to be subjected to a CRC operation and convolutional coding (both described later) is stored in

the transmitter buffer 121 collectively while being split by the processor into bytes. In the following description, such a series of processing performed by the processor to write transmission information to the transmitter buffer 121 will be referred to simply as "block transfer processing."

When writing of all transmission information to the transmitter buffer 121 has completed, the processor feeds a reset signal to the counter 123 and the controlling part 124.

When receiving the reset signal, the counter 123 resets the count value, performs counting at a predetermined cycle, and sequentially outputs addresses as results of the counting.

When receiving the reset signal, the controlling part 124 supplies the selector 128 with a first selection signal indicating that "partial transmission information" (described later) should be selected, and resets the selector 133.

Every time the address that is output from the counter 123 is updated (including being initialized), the controlling part 124 commands the transmitter buffer 121 to read a byte (hereinafter referred to as "partial transmission information") that is stored in a storage area corresponding to a new address among the storage areas of the transmitter buffer 121. Further, the controlling part 124 requests the shift register 122 to load the partial transmission information, and supplies the shift register 122 with a clock signal whose cycle is equal to 1/8 of the above-mentioned cycle.

The shift register 122 sequentially outputs already loaded partial transmission information bit-by-bit in synchronism with this clock signal.

In the CRC operation part 125, unless the above-mentioned first selection signal is updated, the selector 128 selects partial transmission information that is output serially from the shift register 122.

The exclusive-OR gates 129 and 131 and the flip-flops 130-1 to 130-3 generate an FCS (frame check sequence) to be added to the transmission information by dividing a sequence of the above-described partial transmission information by a

generator polynomial  $G(x)$ , which is given by

$$G(x) = x^3 + x^2 + 1.$$

When the address that is output from the counter 123 has reached a predetermined value, the controlling part 124 identifies a point in time when the first bit of an FCS that conforms to the combination of the word length of the transmission information and the above-mentioned generator polynomial  $G(x)$  is obtained, updates the above-mentioned first selection signal, and fixes the logical value that is obtained at the output of the shift register 122 at "0."

In the CRC operation part 125, when the first selection signal is updated, the selector 128 selects, instead of the partial transmission information, the FCS that is sequentially obtained in a serial manner via the flip-flop 130-3.

Therefore, a bit string consisting of the transmission information and the FCS that is added to the tail of transmission information end is obtained at the output of the selector 128 in a serial manner.

On the other hand, in the convolutional coding part 126, the selector 133 alternately selects the outputs of the exclusive-OR gates 132-1 and 132-2 at a frequency that is two times the bit rate of the above-mentioned bit string with the point in time of the resetting by the controlling part 124 employed as a reference.

The exclusive-OR gates 132-1 and 132-2 and the flip-flops 131-1 to 131-3 perform convolutional coding (rate of the code:  $1/2$ ; constraint length: 3) on the above-mentioned bit string by cooperating with the selector 133 while sequentially capturing the bit string bit-by-bit and performing predetermined logical operations.

The interleaver 127 sequentially captures and stores convolutional codes generated by the convolutional coding part 126 through the above convolutional coding. Further, the interleaver 127 performs, on the convolutional codes, interleave processing that is effective in reducing the degree of deterioration in transmission quality due to burst errors that may occur in the transmission channel by reading the

stored convolutional codes bit-by-bit in predetermined order, and generates a transmission sequence.

That is, the CRC operation, the convolutional coding, and the interleave processing, which should be performed  
5 bit-by-bit in a serial manner to generate the transmission sequence, can be performed reliably and efficiently through involvement, only as an information source of transmission information, of a general-purpose processor that is generally not suitable for above kinds of bit-by-bit operations.

10 Incidentally, in the above conventional example, to start a CRC operation that should be performed prior to transmission of transmission information, the processor should perform the above-mentioned block transfer processing prior to the CRC operation.

15 Therefore, actually an individual piece of transmission information is not transmitted until after a lapse of time required for the block transfer processing (halftone-dot-meshed in Figs. 11(A) and 11(B)) in addition to time required for the above-described CRC operation, convolutional coding,  
20 and interleave processing from a point in time when it is recognized, based on a channel control procedure etc., that the individual piece of transmission information should be transmitted.

For desired transmission information to be  
25 parallel/serial-converted on a partial transmission information basis through cooperation among the controlling part 124, the counter 123, and the shift register 133, it is necessary that the transmitter buffer 121 be of a type having a large hardware scale such as a dual port RAM, a FIFO, or a  
30 register file.

The longer the maximum word length of transmission information to be transmitted is, the larger the maximum information content that can be stored in the transmitter buffer 121 is. Therefore, depending on the channel control  
35 procedure, the channel allocation, the zone configuration, and other configurations, there is a possibility that the hardware scale of the transmitter buffer 121 accounts for most of that

of the coding part of Fig. 10.

In general, the block transfer processing and the processor's processing of transmitting the above-mentioned reset signal are performed asynchronously with frames and slots that should be transmitted to a radio transmission channel. Therefore, if the CRC operation, the convolutional coding, and the interleave processing do not complete by the closest transmission time point that follows a point in time when the block transfer processing is started, the transmission of desired transmission information is deferred to the next transmission time point.

Technically, the parallel/serial conversion of transmission information that is performed in the above-described manner under the cooperation among the transmitter buffer 121, the shift register 122, the counter 123, and the controlling part 124 can be realized as processing performed by the processor. However, in general, the processor is required to perform, on a real-time basis, many kinds of processing that should be completed in predetermined periods, such as a channel control. Therefore, it is necessary that the above-mentioned CRC operation, convolutional coding, and interleave processing be performed by dedicated hardware that is provided to reduce the load of the processor.

Where the response speeds of the shift register 122, the counter 123, the controlling part 124, the CRC operation part 125, the convolutional operation section 126, and the interleaver 127 are sufficiently high, it is possible to increase the efficiency of coding and reduce the hardware size by directly loading, into the shift register 122, skipping the transmitter buffer 121, pieces of partial transmission information that are sequentially fed from the processor.

However, to realize a reliable operation for the maximum speed (e.g., 16 MHz) at which the processor can feed partial transmission information, the CRC operation part 125 needs to respond at a speed (128 MHz) that is eight times faster than the above speed and the convolutional coding part 126 and the interleaver 127 need to respond even two times faster (256

MHz).

Realization of circuits capable of operating at such high speeds is prevented by price-related limitations. Even if such limitations are overcome, limitations relating to the thermal designing and the mounting technology still prevent realization of such circuits because of large increase in power consumption.

This problem could be solved by giving higher priority to the block transfer processing and the processing of outputting a reset signal, of processes performed by the processor, or by making the speed at which partial transmission information is fed lower than a predetermined value.

However, if such a measure is taken, in addition to the task (process) configuration that is the structure of processes to be executed by the processor, methods (synchronization among the tasks, communication, etc.) that realize cooperation among the tasks and the combination of these methods would be refined. Therefore, the timing of processes that do not relate to the above problem may also change.

#### **SUMMARY OF THE INVENTION**

An object of the present invention is to provide a coding assisting equipment, a decoding assisting equipment, a radio transmitter, and a radio receiver which can realize desired coding and decoding at high speed with high reliability without the need for changing the basic hardware and software configurations to a large extent.

Another object of the invention is to efficiently realize coding and decoding without the need for providing any means for storing, in advance, all words to be subjected to coding or changing intervals of feeding of those words.

Another object of the invention is to efficiently encode transmission information in parallel operations which are executed word by word.

Another object of the invention is to efficiently decode a received sequence in parallel operations which are executed



word by word.

A still another object of the invention is to efficiently tree-code transmission information in parallel operations which are executed word by word.

- 5       A further object of the invention is to reliably perform desired coding irrespective of the logical values of invalid bit(s) that is/are packed in transmission information.

- 10       Another object of the invention is to reliably perform desired coding as long as words that are fed as transmission information and in which certain invalid bits can be packed and the positions of those invalid bits in the words are known.

- 15       Another object of the invention is to decrease a transmission delay of transmission information that is caused by a long coding time of the transmission information, and to increase the transmission efficiency and the efficiency in the use of a radio transmission channel.

- 20       Still another object of the invention is to increase the service quality and the transmission efficiency of a transmission system without causing large increase in cost or decrease in reliability, enable effective use of not only a transmission channel but also resources for providing a communication service, and make it possible to flexibly accommodate varieties of multiple access systems, channel mappings, zone configurations, modulation systems, channel  
25       control systems, and call setting procedures.

- 30       The above objects can be attained by a coding assisting equipment in which coding is performed sequentially, through a computing unit that is formed as a combinational circuit, on words having a predetermined word length that are obtained by dividing transmission information to be coded.

- 35       In this coding assisting equipment, the operation of coding is performed on split words having the prescribed word length collectively in parallel by the combinational circuit. Therefore, coding is performed efficiently without the need for changing the minimum interval at which the words are fed sequentially or providing a means for storing operation objects prior to the start of the operation as long as the

response time is shorter than the minimum interval.

The above objects are attained by a decoding assisting equipment in which decoding is performed sequentially, through a computing unit that is formed as a combinational circuit, on words having a predetermined word length that are obtained by dividing transmission information to be decoded.

In this decoding assisting equipment, the operation of decoding is performed on split words having the predetermined word length collectively in parallel by the combinational circuit. Therefore, the decoding is performed efficiently without the need for changing the minimum interval at which the words are fed sequentially or providing a means for storing operation objects prior to the start of the operation as long as the response time is shorter than the minimum interval.

Further, the above objects are attained by a radio transmitter and a radio receiver which incorporate one or both of the above coding assisting equipment and/or the decoding assisting equipment.

With these radio transmitters and radio receivers, transmission information is coded and decoded efficiently and transmitted and received on a radio transmission channel. Therefore, there is less deterioration in transmission efficiency due to the large amount of time needed to encode or decode transmission information and there is higher efficiency in the use of radio transmission channels.

Other objects and features of the invention will become apparent from the following description taken in connection with the accompanying drawings.

### **BRIEF DESCRIPTION OF THE DRAWINGS**

Fig. 1 is a block diagram showing principles of coding assisting equipments and decoding assisting equipments according to the present invention;

Fig. 2 is a block diagram showing the principle of a radio transmitter according to the invention;

Fig. 3 is a block diagram showing the principle of a radio receiver according to the invention;

Fig. 4 shows first to third embodiments of the invention;  
Fig. 5 is a table showing the principle of a combinational  
circuit that is provided in a CRC-operation assisting part;

Fig. 6 is a table showing the principle of a combination  
5 circuit that is provided in a coding assisting part;

Fig. 7 shows another configuration of the CRC-operation  
assisting part;

Fig. 8 shows a format of partial transmission  
information that is fed to the CRC-operation assisting part;

10 Fig. 9 shows a fourth embodiment of the invention;

Fig. 10 shows an example configuration of a coding part  
that is incorporated in a mobile station equipment; and

Figs. 11 illustrates problems of a conventional example.

## 15 **DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS**

First, the principles of coding assisting equipments and  
decoding assisting equipments according to the present  
invention will be described with reference to Fig. 1.

Fig. 1 shows the principles of coding assisting  
20 equipments and decoding assisting equipments according to the  
invention. Each of the coding assisting equipments and the  
decoding assisting equipments shown in Fig. 1 is composed of  
all or parts of an operating-object holding section 11, an  
argument holding section 12, an operation section 13 or 21,  
25 a word length adjusting section 32 or 42, and a subsequent  
operation section 31 or 41.

The principle of a first coding assisting equipment  
according to the invention is as follows.

The operating-object holding section 11 sequentially  
30 holds words each consisting of plural bits, and of a constant  
word length. The argument holding section 12 holds an argument  
that should be applied to an operation that is performed on  
a word that is subsequently held by the operating-object  
holding section 11, and that is included in the word being held  
35 by the operating-object holding section 11 and/or the result  
of an operation performed in advance on the word being held  
by the operating-object holding section 11. The operation

section 13 performs, as the operation, in accordance with logical values of individual bits that are included in the word being held by the operating-object holding section 11 and the argument being held by the argument holding section 12, coding  
5 that is defined as a logical operation to be performed on a combination of the logical values.

The operation of the first coding assisting equipment having the above configuration is as follows.

The above-mentioned operation is performed on  
10 sequentially fed individual words having the above-mentioned constant word length collectively in parallel by the operation section 13 that is formed as a combinational circuit.

Therefore, the coding is performed efficiently without the need for changing the minimum interval at which the words  
15 are fed sequentially or providing a means for storing an operation object prior to a start of the operation as long as the sum total of propagation delay times of the operating-object holding section 11, the operation section 13, and the argument holding section 12 is shorter than the minimum  
20 interval or is so short as to be allowable even if it is longer than the minimum interval.

The principle of a second coding assisting equipment according to the invention is as follows.

The operating-object holding section 11 is fed, as the  
25 words, pieces of transmission information divided into words of constant word lengths. The operation section 13 divides the transmission information by a generator polynomial in which the degree of the highest term is smaller than or equal to the constant word length.

30 The operation of the second coding assisting equipment having the above configuration is as follows.

In general, a quotient and a remainder obtained by dividing a transmission information by a generator polynomial in the above-described manner are a linear code or a  
35 algebraic code that is adapted to the generator polynomial.

Therefore, the coding of a transmission information as described above is performed efficiently as parallel

operations that are respectively performed on words having the above-mentioned word length.

The principle of a third coding assisting equipment according to the invention is as follows.

5       The operating-object holding section 11 is fed, as the words, pieces of transmission information divided into units of constant word lengths. The operation section 13 encodes the transmission information according to a tree coding system having a constraint length that is shorter than the constant  
10 word length.

The operation of the third coding assisting equipment having the above configuration is as follows.

Since a constraint length shorter than the above-mentioned word length is applied in the above-mentioned tree  
15 coding, the coding according to the tree coding system is performed sequentially as a parallel logical operation that is performed on a combination of logical values of bits that are included in individual words that are fed in units of the word length and held by the operating-object holding section  
20 11 and an argument held in advance by the argument holding section 12.

Therefore, the tree coding of transmission information can be performed efficiently as parallel operations that are performed on words having the above mentioned word length.

25       The principle of a fourth coding assisting equipment according to the invention is as follows.

The operating-object holding section 11 is fed transmission information that is divided into an integer N of words and is added (an) invalid bit string(s) to one or both  
30 of the most significant end and/or the least significant end. The operation section 13 excludes the invalid bit string(s) from the operation objects.

The operation of the fourth coding assisting equipment having the above configuration is as follows.

35       Invalid bits that are packed in transmission information are excluded from the above-mentioned operation object without altering the basic configuration of a combinational circuit

that is built-in the operation section 13 and performs a predetermined operation.

Therefore, the coding is performed reliably irrespective of the logical values of such invalid bits.

5       The principle of a fifth coding assisting equipment according to the invention is as follows.

10       The operating-object holding section 11 is fed transmission information that is divided into an integer N of words and is added (an) invalid bit string(s) to one or both of the most significant end and/or the least significant end. The operation section 13 employs, as an operation object, valid bit(s) of word(s) that is/are fed as the transmission information and include the invalid bit string.

15       The operation of the fifth coding assisting equipment having the above configuration is as follows.

A combinational circuit that is built in the operation section 13 is given only the above-mentioned valid bits as an operation object.

20       Therefore, the coding is performed reliably as long as words of transmission information in which certain invalid bits may be packed and the positions of the invalid bits in those words are known.

The principle of a sixth coding assisting equipment according to the invention is as follows.

25       The word length adjusting section 32 converts an operation result that is obtained by the operation section 13 into a sequence of words having a constant word length, and sequentially supplies the words to a subsequent operation section 31 for performing a predetermined operation.

30       The operation of the sixth coding assisting equipment having the above configuration is as follows.

A difference in word length between an operation result obtained by the operation section 13 and an operation object on which a predetermined parallel operation should be performed with the operation result by the subsequent operation section 31 is absorbed independently by the word length adjusting section 32.

Therefore, even where the above-mentioned subsequent operation section 31 is disposed as a subsequent stage of the operation section 13, the coding is performed efficiently through cooperation between the operation section 13 and the subsequent operation section 31 without increasing the load of a section for sequentially feeding words having a constant word length to the operation section 13 via the operating-object holding section 11.

The principle of a first decoding assisting equipment according to the invention is as follows.

The operating-object holding section 11 sequentially holds words each consisting of plural bits, and of a constant word length. The argument holding section 12 holds an argument that should be applied to an operation that is performed on a word that is subsequently held by the operating-object holding section 11, and that is included in the word being held by the operating-object holding section 11 and/or a result of the operation performed in advance on the word being held by the operating-object holding section 11. The operation section 21 performs, as the operation, in accordance with logical values of individual bits that are included in the word being held by the operating-object holding section 11 and the argument being held by the argument holding section 12, decoding that is defined as a logical operation to be performed on a combination of the logical values.

The operation of the first decoding assisting equipment having the above configuration is as follows.

The above-mentioned operation is performed on sequentially fed individual words having the above-mentioned constant word length collectively in parallel by the operation section 21 that is formed as a combinational circuit.

Therefore, the decoding is performed efficiently without the need for changing the minimum interval at which the words are fed sequentially or providing a means for storing an operation object prior to a start of the operation as long as the sum total of propagation delay times of the operating-object holding section 11, the operation section 21,

and the argument holding section 12 is shorter than the minimum interval or is so short as to be allowable even if it is longer than the minimum interval.

5 The principle of a second decoding assisting equipment according to the invention is as follows.

The operating-object holding section 11 is fed, as the words, pieces of received sequence divided into units of the constant word lengths. The operation section 21 divides the received sequence by a generator polynomial in which the degree of the highest term is smaller than or equal to the constant word length.

The operation of the second decoding assisting equipment having the above configuration is as follows.

15 In general, a quotient and a remainder obtained by dividing a received sequence by a generator polynomial in the above-described manner mean not only transmission information that is represented by the received sequence but also the form or presence/absence of a bit error in the transmission information.

20 Therefore, the decoding of a received sequence as described above is performed efficiently as parallel operations that are respectively performed on words having the above-mentioned word length.

25 The principle of a third decoding assisting equipment according to the invention is as follows.

The word length adjusting section 42 converts an operation result that is obtained by the operation section 21 into a sequence of words having a constant word length, and sequentially supplies the words to a subsequent operation section 41 for performing a predetermined operation.

The operation of the third decoding assisting equipment having the above configuration is as follows.

30 A difference in word length between an operation result obtained by the operation section 21 and an operation object on which a predetermined parallel operation should be performed with the operation result by the subsequent operation section 41 is absorbed independently by the word



length adjusting section 42.

Therefore, even where the above-mentioned subsequent operation section 41 is disposed as the subsequent stage of the operation section 21, the decoding is performed efficiently through cooperation between the operation section 21 and the subsequent operation section 41 without increasing the load of a means for sequentially feeding words having a constant word length to the operation section 21 via the operating-object holding section 11.

Fig. 2 is a block diagram showing the principle of a radio transmitter according to the invention.

The radio transmitter shown in Fig. 2 is composed of an operating-object holding section 11, an argument holding section 12, an operation section 13, and a wireless interfacing section 51.

The principle of the radio transmitter according to the invention is as follows.

The operating-object holding section 11 sequentially holds words each consisting of plural bits, and of a constant word length. The argument holding section 12 holds an argument that should be applied to an operation that is performed on a word that is subsequently held by the operating-object holding section 11, and that is included in the word being held by the operating-object holding section 11 and/or a result of the operation performed in advance on the word being held by the operating-object holding section 11. The operation section 13 performs, as the operation, in accordance with logical values of individual bits that are included in the word being held by the operating-object holding section 11 and the argument being held by the argument holding section 12, coding that is defined as a logical operation to be performed on a combination of the logical values. The wireless interfacing section 51 transmits a result of the operation performed by the operation section 13 to a radio transmission channel.

In the above-configured radio transmitter, transmission information that is fed as a sequence of words as described above is encoded efficiently by the operation section 13 and

transmitted to a radio transmission channel via the wireless interfacing section 51.

Therefore, a delay of transmission of such transmission information due to the fact that long time is needed to encode the transmission information is reduced and the transmission efficiency and the efficiency of use of a radio transmission channel is increased.

Fig. 3 is a block diagram showing the principle of a radio receiver according to the invention.

The radio receiver shown in Fig. 3 is composed of a wireless interfacing section 61, an operating-object holding section 62, an argument holding section 63, and an operation section 64.

The principle of the radio receiver according to the invention is as follows.

The wireless interfacing section 61 demodulates a radio-frequency signal that has been transmitted on a radio transmission channel, and divides transmission information that is given as the radio-frequency signal into words each consisting of plural bits and of a constant word length and outputs the words. The operating-object holding section 62 sequentially holds the words that are output from the wireless interfacing section 61. The argument holding section 63 holds an argument that should be applied to an operation that is performed on a word that is subsequently held by the operating-object holding section 62, and that is included in the word being held by the operating-object holding section 62 and/or the result of the operation performed in advance on the word being held by the operating-object holding section 62. The operation section 64 performs, as the operation, in accordance with logical values of individual bits that are included in the word being held by the operating-object holding section 62 and the argument being held by the argument holding section 63, decoding that is defined as a logical operation to be performed on a combination of the logical values.

In the above-configured radio receiver, transmission information that is received via a radio transmission channel

is decoded efficiently under cooperation among the wireless interfacing section 61, the operating-object holding section 62, the argument holding section 63, and the operation section 64.

Therefore, a transmission delay due to the fact that long time is needed to decode such transmission information is reduced and the transmission efficiency and the efficiency of use of a radio transmission channel is increased.

Embodiments of the present invention will be hereinafter described in detail with reference to the accompanying drawings.

Fig. 4 shows first to third embodiments of the invention.

These embodiments are different from the conventional example of Fig. 10 in that the transmitter buffer 121, the shift register 122, the counter 123, and the controlling part 124 are not provided, that a CRC-operation assisting part 70 is provided in place of the CRC operation part 125, that a coding assisting part 71 is provided in place of the convolutional coding part 126, that an interleaver 72 is provided in place of the interleaver 127, and that the output of the CRC-operation assisting part 70 and the input of the coding assisting part 71 are connected to corresponding input/output ports of a processor (not shown).

The CRC-operation assisting part 70 is composed of a buffer 74 the input of which is connected to a first output port of the processor; a read-clock generating part 75 the input of which is connected to a second output port of the processor and a first output of which is connected to a control input of the buffer 74; flip-flops (FFs) 76-1 to 76-8 the inputs of which are directly connected to eight parallel outputs of the buffer 74; an inverter 77 the input of which is directly connected to a second output of the read-clock generating part 75; flip-flops (FFs) 78-0 to 78-2 reset terminals of which are directly connected to the output of the inverter 77, enable terminals of which are directly connected to a third output of the read-clock generating part 75, and that are disposed as the final stage; an exclusive-OR gate 79-1 having the output

that is directly connected to a load terminal of the flip-flop 78-0 as well as seven inputs that are directly connected to the outputs of the respective flip-flops 76-1, 76-4, 76-6 to 76-8, 78-1, and 78-2; an exclusive-OR gate 79-2 having the  
5 output that is directly connected to a load terminal of the flip-flop 78-1 as well as five inputs that are directly connected to the outputs of the respective flip-flops 76-3, 76-5 to 76-7, and 78-0; and an exclusive-OR gate 79-3 having the output that is directly connected to a load terminal of  
10 the flip-flop 78-2 as well as five inputs that are directly connected to the outputs of the respective flip-flops 76-1, 76-2, 76-7, 76-8, and 78-2.

The coding assisting part 71 is composed of a buffer 80 the input of which is connected to a third output port of the  
15 processor; a clock generating section 81 the input of which is connected to a fourth output port of the processor and one output of which is directly connected to a control input of the buffer 80; flip-flops (FFs) 82-1 to 82-8 the inputs of which are connected to respective eight parallel outputs of the  
20 buffer 80; a delay circuit (D) 83 the input of which is directly connected to the other output of the clock generating section 81; flip-flops (FFs) 84-0 and 84-1 reset terminals of which are directly connected to the output of the delay circuit 83 and the inputs of which are connected to the outputs of the  
25 respective flip-flops 82-7 and 82-8; an exclusive-OR gate 85-1 having two inputs that are directly connected to the outputs of the respective flip-flops 82-1 and 84-0; an exclusive-OR gate 85-2 having two inputs that are directly connected to the outputs of the respective flip-flops 82-1 and 84-1; an  
30 exclusive-OR gate 85-3 having two inputs that are directly connected to the outputs of the respective flip-flops 82-1 and 82-2; an exclusive-OR gate 85-4 having two inputs that are directly connected to the outputs of the respective flip-flops 82-2 and 84-0; an exclusive-OR gate 85-5 having two inputs that  
35 are directly connected to the outputs of the respective flip-flops 82-2 and 82-3; an exclusive-OR gate 85-6 having two inputs that are directly connected to the outputs of the

5        respective flip-flops 82-1 and 82-3; an exclusive-OR gate 85-7  
      having two inputs that are directly connected to the outputs  
      of the respective flip-flops 82-3 and 82-4; an exclusive-OR  
10    gate 85-8 having two inputs that are directly connected to the  
      outputs of the respective flip-flops 82-2 and 82-4; an  
      exclusive-OR gate 85-9 having two inputs that are directly  
      connected to the outputs of the respective flip-flops 82-4 and  
      82-5; an exclusive-OR gate 85-10 having two inputs that are  
15    directly connected to the outputs of the respective flip-flops  
      82-3 and 82-5; an exclusive-OR gate 85-11 having two inputs  
      that are directly connected to the outputs of the respective  
      flip-flops 82-5 and 82-6; an exclusive-OR gate 85-12 having  
      two inputs that are directly connected to the outputs of the  
      respective flip-flops 82-4 and 82-6; an exclusive-OR gate  
20    85-13 having two inputs that are directly connected to the  
      outputs of the respective flip-flops 82-6 and 82-7; an  
      exclusive-OR gate 85-14 having two inputs that are directly  
      connected to the outputs of the respective flip-flops 82-5 and  
      82-7; an exclusive-OR gate 85-15 having two inputs that are  
      directly connected to the outputs of the respective flip-flops  
      82-7 and 82-8; an exclusive-OR gate 85-16 having two inputs  
      that are directly connected to the outputs of the respective  
      flip-flops 82-6 and 82-8; and flip-flops (FFs) 86-1 to 86-  
25    16 that are disposed, as the final stage, subsequent stage of  
      the respective exclusive-OR gates 85-1 to 85-16.

      The operation of the first embodiment of the invention  
will be described below.

30        In the CRC-operation assisting part 70, when receiving  
      a reset signal from the processor, the read-clock generating  
      part 75 resets the flip-flops 78-0 to 78-2 via the inverter  
      77. To simplify the description, it is assumed that all of  
      the flip-flops 78-0 to 78-2 are reset by this resetting.

35        The read-clock generating part 75 detects a write enable  
      signal that is fed from the processor every time partial  
      transmission information is output from the processor, and  
      supplies the write enable signal to the buffer 74.

      The buffer 74 captures the partial transmission

information that is output from the processor at a point in time of reception of the write enable signal, and stores the partial transmission information.

5 The partial transmission information thus stored in the buffer 74 is copied to the flip-flops 76-1 to 76-8 automatically and quickly.

Incidentally, the number of bits that can be stored parallel in the flip-flops 78-0 to 78-2 is equal to a word length "3" of an FCS that is calculated by the CRC operation part 125 shown in Fig. 10 and determined based on the above-described generator polynomial  $G(x)$ .

Where the logical values of initial values that are set in the flip-flops 78-0 to 78-2 are  $i_0$ ,  $i_1$ , and  $i_2$ , respectively, and the logical values of the eight bits of partial transmission information that are serially supplied to the CRC operation part 125 after determination of the above initial values are  $d_1$ ,  $d_2$ ,  $d_3$ ,  $d_4$ ,  $d_5$ ,  $d_6$ ,  $d_7$ , and  $d_8$  in time-series order that is represented by  $t$  ( $= 1$  to  $8$ ),

(a) a logical value obtained at the output of the exclusive-OR gate 129,

(b) logical values held by the respective flip-flops 130-1 and 130-2,

(c) a logical value obtained at the output of the exclusive-OR gate 131, and

25 (d) a logical value held by the flip-flop 130-3 are given in time-series order by logical formulae shown in Fig. 5. In Fig. 5, a symbol, which is a mark "+" with a circle around it, means an operator of exclusive-OR.

In Fig. 5, in general, among the operation objects of the exclusive-OR operations that produce the above logical values (a)-(d), omission can be made for operation objects that are redundant in an even number.

Specifically, in the dividing circuit that is composed of the flip-flops 130-1 to 130-3 and the exclusive-OR gates 129 and 131 shown in Fig. 10, the logical values held by the respective flip-flops 130-1 to 130-3 are uniquely determined as  $I_0$ ,  $I_1$ , and  $I_2$  as halftone-dot-meshed in Fig. 5 at a point

in time when the eight bits of partial transmission information having respective logical values d1, d2, d3, d4, d5, d6, d7, and d8 have been fed sequentially in a serial manner.

On the other hand, in the CRC-operation assisting part 70, the above logical values i0-i2 are given as logical values held by the respective flip-flops 78-0 to 78-2 and the logical values d1, d2, d3, d4, d5, d6, d7, and d8 are given as logical values held by the respective flip-flops 76-1 to 76-8.

Further, the exclusive-OR gates 79-1 to 79-3 perform, according to the logical values i0-i2 and d1-d8, exclusive-OR operations that collectively obtain I0, I1, and I2 that are given by logical formulae shown in Fig. 5.

The logical values i0-i2 are set at "0" immediately after resetting. However, when a certain operation has been performed in advance by the exclusive-OR gates 79-1 to 79-3, the logical value I0, I1, and I2 are delivered as the operation results.

Every time a write enable signal (described above) is fed from the processor, the read-clock generating part 75 feeds an enable signal to the flip-flops 78-0 to 78-2 at a point in time that is delayed from the point in time of the feeding of the write enable signal by more than a propagation delay time of the buffer 74, the flip-flops 76-1 to 76-8, and the exclusive-OR gates 79-1 to 79-3.

When receiving the enable signal, the flip-flops 78-0 to 78-2 hold the logical values I0, I1, and I2 that are output from the respective exclusive-OR gates 79-1 to 79-3 at this point in time.

The logical values I0, I1, and I2 are referred to, as results that were determined for partial transmission information that was fed from the processor in advance, during the course of similar operations on partial transmission information that will be fed subsequently.

After feeding all pieces of partial transmission information (a predetermined number of bytes) to the CRC-operation assisting part 70, the processor reads an FSC that is held by the flip-flops 78-0 to 78-2, and generates a bit

string (hereinafter referred simply as "CRC code") in which the FSC is added to the sequence of those pieces of partial transmission information.

Further, the processor feeds a reset signal to the coding assisting part 71, and sequentially feeds, to the coding assisting part 71, a write enable signal and a "partial CRC code" obtained by dividing the above CRC code into bytes.

In the coding assisting part 71, the buffer 80, the clock generating section 81, the delay circuit 83, and the flip-flops 82-1 to 82-8, 84-0, and 84-1 operate in cooperation with the processor like the buffer 74, the read-clock generating part 75, the inverter 77, and the flip-flops 76-1 to 76-8 and 78-0 to 78-2 of the CRC-operation assisting part 70 do. Their detailed operations will be described below.

Incidentally, the number of bits that can be stored parallel in the flip-flops 84-0 and 84-1 is set in advance at "3," which is equal to the word length of a bit string that is held by the flip-flops 131-1 to 131-3 during the course of the operation performed by the convolutional coding part 126 shown in Fig. 10.

Where the logical values of initial values that are set in the flip-flops 84-0 and 84-1 are c0 and c1, respectively, and the logical values of the 8 bits of a partial CRC code that are fed serially after determination of those initial values are f1, f2, f3, f4, f5, f6, f7, and f8 in time-series order that is represented by t (= 1 to 8),

(A) logical values held by the respective flip-flops 131-1 to 131-3, and

(B) logical values obtained at the outputs of the respective exclusive-OR gates 132-1 and 132-2 are given in time-series order as shown in Fig. 6. In Fig. 6, a symbol, which is a mark "+" with a circle around it, means an operator of exclusive-OR.

That is, in the convolutional coding part 126 shown in Fig. 10, during the course that the eight bits of a partial CRC code word having logical values f1, f2, f3, f4, f5, f6, f7, and f8 are given sequentially in a serial manner, the



logical values of a convolutional code that is obtained under the cooperation among the exclusive-OR gates 132-1 and 132-2 and the selector 133 in accordance with a combination of logical values held by the respective flip-flops 131-1 to 131-3 are uniquely determined as g1, g2, g3, g4, g5, g6, g7, g8, g9, g10, g11, g12, g13, g14, g15, and g16 that are halftone-dot-meshed in Fig. 6.

In the coding assisting part 71, the exclusive-OR gates 85-1 to 85-16 perform, on the logical values c0 and c1 held by the flip-flops 84-0 and 84-1 and the logical values f1, f2, f3, f4, f5, f6, f7, and f8, exclusive-OR operations that collectively determine logical values g1-g16 that are given by the respective formulae shown in Fig. 6.

Both of the above-mentioned logical values c0 and c1 are set at "0" immediately after resetting. However, when certain operations have been performed in advance by the exclusive-OR gates 85-1 to 85-16, the logical values C0 and C1 are delivered as results C0 and C1 of the operations.

The logical values g1, g2, g3, g4, g5, g6, g7, g8, g9, g10, g11, g12, g13, g14, g15, and g16 are held by the respective flip-flops 86-1 to 86-16.

Among the logical values f1, f2, f3, f4, f5, f6, f7, and f8 held by the respective flip-flops 82-1 to 82-8, the logical values f7 and f8 are, as included in the logical formulae shown in Fig. 6 that give the logical values g1, g2, and g4, held by the respective flip-flops 84-0 and 84-1 as operation objects of operations that will be performed in a similar manner on a partial CRC code word that will be fed subsequently.

The interleaver 72 generates a transmission sequence by sequentially capturing partial convolutional codes each of which is given as a sequence of 16-bit logical values g1, g2, g3, g4, g5, g6, g7, g8, g9, g10, g11, g12, g13, g14, g15, and g16 in accordance with each partial CRC code that is fed from the processor and performing processing that is equivalent to the interleave processing performed by the interleaver 127 shown in Fig. 10.

That is, the CRC operation and the convolutional coding

are performed sequentially and quickly by the combinational circuits that perform parallel operations in accordance with partial transmission information and partial CRC code words that are fed from the processor on a byte-by-byte basis.

5       Partial transmission information and partial CRC code words are used as operation objects of the CRC operation and the convolutional coding unlike the conventional case in which they are collectively stored in the transmitter buffer and then read sequentially.

10       Among the pieces of software that are built in the process that feeds partial transmission information and partial CRC code words, the configuration of software that realizes the CRC-operation assisting part 70 need not be modified to a large extent as long as the sum total of propagation delay times of  
15 the buffer 74, the flip-flops 76-1 to 76-8, the exclusive-OR gates 79-1 to 79-3, and the flip-flops 78-0 to 78-2 is shorter than the bus cycle of the processor or is so short as to be allowable.

20       The configuration of software that realizes the coding assisting part 71 need not be modified to a large extent as long as the sum total of propagation delay times of the buffer 80, the flip-flops 82-1 to 82-8, the exclusive-OR gates 85-1 to 85-16, and the flip-flops 86-1 to 86-16 is shorter than the bus cycle of the processor or is so short as to be allowable.

25       Therefore, according to this embodiment, the hardware scale can be reduced and a transmission sequence can be generated efficiently without the need for modifying the hardware and software configurations to a large extent.

30       In this embodiment, the CRC-operation assisting part 70 realizes an efficient CRC operation by operating under the above-described processor. However, the invention is not limited to such a CRC operation and can similarly be applied to coding that uses any of various linear codes that include not only cyclic codes but also algebraic codes such as the BCH  
35 code that conforms to the Galois field theory.

      In this embodiment, the coding assisting part 71 realizes efficient convolutional coding by operating under the

processor. However, the invention is not limited to such convolutional coding and can be applied to any tree coding irrespective of the constraint length and the rate of the code as long as a result of coding of each of bit strings that are  
5 given in the form of divided words having a predetermined word length is uniquely determined for the logical values of the bit string and a result can be determined by a combinational circuit.

10 A second embodiment of the invention will be hereinafter described.

The second embodiment is different, in configuration, from the first embodiment in that a CRC-operation assisting part 90 shown in Fig. 7 is provided in place of the CRC-operation assisting part 70.

15 The CRC-operation assisting part 90 is different, in configuration, from the CRC-operation assisting part 70 in that a read-clock generating part 75A having a control output that is directly connected to the control terminals of the respective exclusive-OR gates 79-1 to 79-3 is provided in place  
20 of the read-clock generating part 75, and that an exceptional processing part 91 is provided having an input terminal that is directly connected to the outputs of the respective flip-flops 76-1, 76-2, 78-0, 78-1, and 78-2, output terminals that are directly connected to the load terminals of the  
25 respective flip-flops 78-0 to 78-2, together with the outputs of the respective exclusive-OR gates 79-1 to 79-3 and a control terminal to which a particular output of the read-clock generating part 75A is directly connected.

As indicated by hatched halftone dot meshing in Fig. 5,  
30 the exceptional processing part 91 is composed of an exclusive-OR gate 92-1 having the input that is directly connected to the outputs of the respective flip-flops 76-1, 76-2, 78-1, and 78-2 and the output that is directly connected to the load terminal of the flip-flop 78-0, an exclusive-OR  
35 gate 92-2 having the input that is directly connected to the outputs of the respective flip-flops 76-1 and 78-2 and the output that is directly connected to the load terminal of the

flip-flop 78-1, and an exclusive-OR gate 92-3 having the input that is directly connected to the outputs of the respective flip-flops 76-1, 76-2, 78-0, 78-1 and 78-2 and the output that is directly connected to the load terminal of the flip-flop 78-2.

The operation of the second embodiment of the invention will be described below with reference to Figs. 4 and 7.

In this embodiment, as shown in Fig. 8, the processor sequentially feeds, to the buffer 74, pieces of partial transmission information consisting of a first byte in which valid bits are packed in only the higher two bits and second and third bytes in each of which valid eight bits are packed.

The read-clock generating part 75A counts write enable signals that are fed from the processor starting from a point in time when a reset signal is fed from the processor.

Further, during a period when the count value is "1," the read-clock generating part 75A allows operation of the exceptional processing part 91 and prohibits the exclusive-OR gates 79-1 to 79-3 from performing logical operations. During a period when the count value is "2" or "3," the read-clock generating part 75A prohibits operation of the exceptional processing part 91 and allows the exclusive-OR gates 79-1 to 79-3 to perform logical operations.

That is, during a period when the above-mentioned first byte as partial transmission information is fed from the processor, only the valid higher two bits of the partial transmission information are used as an operation object. Therefore, the CRC operation is performed correctly even if information of any logical values is packed in the lower six bits of the first byte.

In this embodiment, the exceptional processing part 91 is added on condition that invalid bits of the first byte are excluded from an operation object. Errors that might otherwise occur in a result of the CRC operation due to such invalid bits are avoided by the exceptional processing part 91's operating in place of the exclusive-OR gates 79-1 to 79-3.

However, where invalid bits are packed in only a higher

degree of the first byte and the logical values of all the invalid bits are "0," the CRC-operation assisting part 70 shown in Fig. 4 may be provided in place of the CRC-operation assisting part 90 shown in Fig. 7.

5       Where invalid bits are packed in one or both of a high degree of the first byte and a lower degree of the third byte and any of the logical values of those invalid bits is "1," there may be provided an operation circuit that performs a logical operation that is adapted to pieces of partial  
10   transmission information that are fed as only the first and third bytes or an operation circuit that invalidates, when necessary, bits that should be input to an operation circuit that performs a logical operation adapted to partial transmission information that is fed as the second byte in  
15   place of the exclusive-OR gates 79-1 to 79-3.

A third embodiment of the invention will be hereinafter described.

The third embodiment is different, in configuration, from the first embodiment in that, as indicated by a broken  
20   line in Fig. 4, the outputs of the CRC-operation assisting part 70 and the inputs of the coding assisting part 71 are connected to none of the input/output ports of the processor, a word length adjusting part 73 is provided between the CRC-operation assisting part 70 and the coding assisting part 71, and  
25   transmission information inputs of the word length adjusting part 73 are connected in parallel to the inputs of the buffer 74.

The operation of the third embodiment will be described below with reference to Fig. 4.

30       Since the operations that the CRC-operation assisting part 70 performs in cooperation with the processor are the same as in the first embodiment, they are not described here.

The word length adjusting part 73 captures, instead of the processor, partial transmission information that was fed  
35   from the processor to the CRC-operation assisting part 70 and an FCS that is obtained by the CRC-operation assisting part 70, and stores those.

Further, the word length adjusting part 73 converts a CRC code that consists of the partial transmission information sequence and the FCS into a sequence of partial CRC code words (described above) and sequentially supplies the latter to the coding assisting part 71.

That is, according to this embodiment, the operation of the convolutional coding that should be performed after the CRC operation is performed reliably because the processing that is performed by the processor in the first and second embodiments is performed here by the word length adjusting part 73.

This reduces the load of the processor and prevents a transmission sequence from being generated with an undue delay due to an overload of the processor.

In each of the above embodiments, the invention is applied to the coding for generating a transmission sequence. However, the application range of the invention is not limited to such a coding process and the invention can similarly be applied to decoding of a received sequence as long as the above-mentioned word length conforms to the degree, the constraint length, and the rate of the code of a desired generator polynomial and one or both of division based on the generator polynomial and tree decoding are performed during the course of the decoding.

Fig. 9 shows a fourth embodiment of the invention.

As shown in Fig. 9, the input of a receiving part 102 is connected to the feeding point of an antenna 101-R and the output of the receiving part 102 is connected to a demodulation input of a modulation/demodulation part 103. A demodulation output of the modulation/demodulation part 103 is connected to a demodulation input of a developing/inserting section 104. A modulation output of the developing/inserting section 104 is connected to a modulation input of the modulation/demodulation part 103. A modulation output of the modulation/demodulation part 103 is connected to the feeding point of an antenna 101-T via a transmitting part 105. Corresponding outputs of a synthesizer section 106 are

connected to local oscillation inputs of the transmitting part 105 and the receiving part 102. Corresponding input/output ports of a processor (CPU) 107 are connected to control input/output terminals of the receiving part 102, the modulation/demodulation part 103, the developing/inserting section 104, the transmitting part 105, and the synthesizing section 106. A speaker 108 and a microphone (not shown) are connected to analog ports of the developing/inserting section 104, and a facsimile terminal 109, a personal computer 110, and other terminals are connected to digital ports of the developing/inserting section 104.

The modulation/demodulation part 103 is composed of a slot assembling part 111, de-interleaver 112, a Viterbi decoder 113, and a CRC part 114 that are cascade between the above-mentioned demodulation input and demodulation output and operate under the processor 107, and an FCS-adding part 115, a convolutional coding part 116, an interleaver 117, and a slot disassembling part 118 that are cascade between the above-mentioned modulation input and modulation output and operate under the processor 107.

The operation of the fourth embodiment will be described below.

The basic operations of the individual sections are as follows.

The processor 107 takes a leading part in a channel control by cooperating with the developing/inserting section 104 and the modulation/demodulation part 103 as well as the receiving part 102, the transmitting part 105, and the synthesizer section 106.

During the course of such a channel control, the processor 107 instructs the synthesizer section 106 to generate a local oscillation signal having a frequency that conforms to a predetermined channel mapping and zone configuration.

A received wave that has been transmitted from a radio base station that forms a wireless zone where the local station exists and has reached the antenna 101-R is converted by the

receiving part 102 that operates in accordance with the above-mentioned local oscillation signal into a predetermined intermediate frequency signal, which is converted into a baseband signal (hereinafter referred to as "downward baseband signal") through demodulation.

5 In the modulation/demodulation part 103, the slot assembling part 111 extracts a sequence of slots that are designated by the processor 107 under the above-mentioned channel control from slots that are included in the downward  
10 baseband signal in a predetermined form and assembles those, and thereby generates a bit string representing transmission information (hereinafter referred to as "downward transmission information") that has been received on a particular radio channel (e.g., a perch channel on which the  
15 local station is waiting).

The de-interleaver 112, the Viterbi decoder 113, and the CRC part 114 restores the downward transmission information by performing de-interleave processing, convolutional decoding, and CRC processing on the bit string.

20 The de-interleave processing, the convolutional decoding, and the CRC processing are kinds of processing that are reversible with respect to a CRC operation, convolutional coding, and interleave processing that the radio base station performed on transmission information to generate a  
25 transmission sequence to be transmitted on the above-mentioned particular channel.

The developing/inserting section 104 performs delivering of the downward transmission information between the processor 107 or the facsimile terminal 109 (or the  
30 personal computer 110) and the CRC part 114 in units of a predetermined word length (for simplification, here it is assumed to be a byte).

Further, by performing processing that is reverse to the processing that realizes the above-mentioned delivering under  
35 the processor 107, the developing/inserting section 104 supplies, to the modulation/demodulation part 103, in units of a predetermined word length, transmission information



(hereinafter referred to as "upstream transmission information") that is fed from the processor 107 or the facsimile terminal 109 (or the personal computer 110) and is to be transmitted to the radio base station.

5 In the modulation/demodulation part 103, the FCS-adding part 115, the convolutional coding part 116, the interleaver 117, and the slot disassembling part 118 perform, on the thus-fed transmission information, processing that is reverse to the processing that was performed in the above-described  
10 manner by the CRC part 114, the Viterbi decoder 113, the de-interleaver 112, and the slot assembling part 111, and thereby generates a baseband signal (hereinafter referred to as "upstream baseband signal") that includes the upstream transmission information and consists of a bit string that  
15 should be located in predetermined slots.

The synthesizer section 106 generates a local oscillation signal to be used for transmission in accordance with a command that is supplied from the processor 107 according to a channel control procedure.

20 The transmitting part 105 generates a transmission wave by performing, in accordance with the upstream baseband signal and the local oscillation signal, processing that is reverse to the processing that was performed in the above-described manner by the receiving part 102, and transmits the generated  
25 transmission wave to the radio base station via the antenna 101-T.

Incidentally, in this embodiment, the FCS-adding part 115, the convolutional coding part 116, and the interleaver 117 that are provided in the modulation/demodulation part 103  
30 cooperate with the processor 107 and the developing/inserting section 104 that operates under the processor 107 as indicated by a two-dot chain line in Fig. 9, and are configured as the CRC-operation assisting part 70, the coding assisting part 71, and the interleaver 72 shown in Fig. 4, respectively.

35 That is, each of the CRC operation and the convolutional coding is performed at high speed by a combinational circuit that performs parallel operations on a byte-by-byte basis

without making the hardware scale larger than in the conventional example or greatly modifying the hardware configuration from the conventional example.

Therefore, this embodiment makes it possible to flexibly adapt to a multiple access system, a channel mapping, and a zone configuration that are employed and to perform efficient channel control without changing the basic configuration of software that is built in the processor 107 or greatly increasing the power consumption.

In this embodiment, the invention is applied to the FCS-adding part 115, the convolutional coding part 116, and the interleaver 117 that serve for transmission among the components of the modulation/demodulation part 103.

However, the application range of the invention is not limited to the FCS-adding part 115, the convolutional coding part 116, and the interleaver 117. For example, where the de-interleaver 112 outputs a received sequence by dividing it into bytes, the invention may be applied to one or both of the Viterbi decoder 113 and the CRC part 114. Where the Viterbi decoder 113 outputs, with dividing into bytes, a bit string that is obtained by decoding such a received sequence, the invention may be applied to the CRC part 114.

In this embodiment, the invention is applied to the terminal equipment of a mobile communication system to which the CDMA scheme is applied. However, the application range of the invention is not limited to such a multiple access system and the invention can similarly be applied to radio transmission systems to which the TDMA system or the FDMA system is applied.

In this embodiment, no specific description is made of a modulation system that is applied to a radio transmission channel as well as of the above-described channel mapping and zone configuration, the channel mapping, the zone configuration, and the modulation system may be of any kind.

In each of the above embodiments, the above-mentioned word length is set at a single byte. However, the word length may be set at any value as long as division based on a

predetermined generator polynomial or tree coding is performed so as to conform to the degree, the rate of the code, and the constraint length of a desired generator polynomial as in the case of, for example, coding or decoding of a block code in  
5 a process of one or both of generation of a transmission sequence and demodulation of a received sequence.

Further, the invention is not limited to the above embodiments and a variety of embodiments are possible without departing from the spirit and scope of the invention. Any  
10 improvements may be made in part or all of the constituent sections.

## CLAIMS

WHAT IS CLAIMED IS:

1. A coding assisting equipment comprising:  
operating-object holding means for sequentially holding  
5 each word respectively consisting of plural bits, and of  
constant word lengths;  
argument holding means for holding an argument that  
should be applied to an operation that is performed on a word  
that is subsequently held by said operating-object holding  
10 means, and that is included in said word being held by said  
operating-object holding means and/or the result of an  
operation performed in advance on the word being held by said  
operating-object holding means; and  
operation means for performing, as said operation, in  
15 accordance with logical values of individual bits that are  
included in said word being held by said operating-object  
holding means and said argument being held by said argument  
holding means, coding that is defined as a logical operation  
to be performed on a combination of said logical values.  
20 2. A decoding assisting equipment comprising:  
operating-object holding means for sequentially holding  
each word respectively consisting of plural bits, and of  
constant word lengths;  
argument holding means for holding an argument that  
25 should be applied to an operation that is performed on a word  
that is subsequently held by said operating-object holding  
means, and that is included in said word being held by said  
operating-object holding means and/or results of an operation  
performed in advance on the word being held by said  
30 operating-object holding means; and  
operation means for performing, as said operation, in  
accordance with logical values of individual bits that are  
included in said word being held by said operating-object  
holding means and said argument being held by said argument  
35 holding means, coding that is defined as a logical operation  
to be performed on a combination of said logical values.  
3. A coding assisting equipment according to claim 1,

wherein said operating-object holding means is fed with, as said words, pieces of transmission information divided into units of said constant word lengths, and wherein said operation means divides said transmission information by a generator polynomial in which a degree of the highest term is smaller than or equal to said word length.

4. A decoding assisting equipment according to claim 2, wherein said operating-object holding means is fed with, as said words, pieces of received sequence divided into units of said constant word lengths, and wherein said operation means divides said received sequence by a generator polynomial in which a degree of the highest term is smaller than or equal to said word length.

5. A coding assisting equipment according to claim 1, wherein said operating-object holding means is fed with, as said words, pieces of transmission information divided into units of said constant word lengths, and wherein the operation means tree encodes said transmission information with a constraint length that is shorter than said constant word length.

6. A coding assisting equipment according to claim 3, wherein said operating-object holding means is fed with transmission information that is divided into an integer N of words and is added (an) invalid bit strings(s) to one or both of the most significant end and/or the least significant end, and wherein said operation means excludes said invalid bit string(s) from the operation objects.

7. A coding assisting equipment according to claim 3, wherein said operating-object holding means is fed with transmission information that is divided into an integer N of words and is added (an) invalid bit strings(s) to one or both of the most significant end and/or the least significant end, and wherein the operation means employs, as an operation object, valid bit(s) of word(s) that is/are fed as said transmission information and include said invalid bit string.

8. A coding assisting equipment according to claim 1, further comprising word length adjusting means for converting

an operation result that is obtained by said operation means into a sequence of words having a constant word length, and for sequentially supplying the words to a subsequent operation means for performing a predetermined operation.

5 9. A coding assisting equipment according to claim 3, further comprising word length adjusting means for converting an operation result that is obtained by said operation means into a sequence of words having a constant word length, and for sequentially supplying the words to a subsequent operation  
10 means for performing a predetermined operation.

10. A coding assisting equipment according to claim 5, further comprising word length adjusting means for converting an operation result that is obtained by said operation means into a sequence of words having a constant word length, and  
15 for sequentially supplying the words to a subsequent operation means for performing a predetermined operation.

11. A coding assisting equipment according to claim 6, further comprising word length adjusting means for converting an operation result that is obtained by said operation means  
20 into a sequence of words having a constant word length, and for sequentially supplying the words to a subsequent operation means for performing a predetermined operation.

12. A coding assisting equipment according to claim 7, further comprising word length adjusting means for converting  
25 an operation result that is obtained by said operation means into a sequence of words having a constant word length, and for sequentially supplying the words to a subsequent operation means for performing a predetermined operation.

13. A decoding assisting equipment according to claim 2,  
30 further comprising word length adjusting means for converting an operation result that is obtained by said operation means into a sequence of words having a constant word length, and for sequentially supplying the words to a subsequent operation means for performing a predetermined operation.

35 14. A decoding assisting equipment according to claim 4, further comprising word length adjusting means for converting an operation result that is obtained by said operation means

into a sequence of words having a constant word length, and for sequentially supplying the words to a subsequent operation means for performing a predetermined operation.

15. A radio transmitter comprising:

5     operating-object holding means for sequentially holding each word respectively consisting of plural bits, and of constant word lengths;

argument holding means for holding an argument that should be applied to an operation that is performed on a word  
10     that is subsequently held by said operating-object holding means, and that is included in said word being held by said operating-object holding means and/or results of an operation performed in advance on the word being held by said operating-object holding means;

15     operation means for performing, as said operation, in accordance with logical values of individual bits that are included in said word being held by said operating-object holding means and said argument being held by said argument holding means, coding that is defined as a logical operation  
20     to be performed on a combination of said logical values; and  
wireless interfacing means for transmitting the result of said operation performed by said operation means to a radio transmission channel.

16. A radio receiver comprising:

25     wireless interfacing means for demodulating a radio-frequency signal reached through a radio transmission channel, and for dividing transmission information that is given as said radio-frequency signal into words each consisting of plural bits and of a constant word length and for outputting the words;

30     operating-object holding means for sequentially holding said words that are output from said wireless interfacing means;

argument holding means for holding an argument that should be applied to an operation that is performed on a word  
35     that is subsequently held by said operating-object holding means, and that is included in said word being held by said operating-object holding means and/or the result of an

operation performed in advance on the word being held by said operating-object holding means; and

operation means for performing, as said operation, in accordance with logical values of individual bits that are  
5 included in said word being held by said operating-object holding means and said argument being held by said argument holding means, coding that is defined as a logical operation to be performed on a combination of said logical values.



# **ABSTRACT OF THE DISCLOSURE**

A coding assisting equipment is provided in which transmission information is fed in such a manner as to be divided into words having a predetermined word length and is  
5 coded collectively through a computing unit that is formed as a combinational circuit. A decoding assisting equipment is provided in which a received sequence is fed in such a manner as to be divided into words having a predetermined word length and is decoded collectively through a computing unit that is  
10 formed as a combinational circuit. A radio transmitter and a radio receiver are provided that incorporates the above coding assisting equipment and the decoding assisting equipment, respectively. In a transmission system to which the invention is applied, the service quality and the  
15 transmission efficiency are increased in an inexpensive manner, resources are utilized effectively, and flexible application of a variety of systems is enabled.

FIG. 1




FIG. 2





FIG. 3



# FIG. 4





FIG. 5

	LOGICAL VALUE OBTAINED AT THE OUTPUT OF THE EXCLUSIVE-OR GATE 129	LOGICAL VALUE HELD BY THE FLIP-FLOP 130-1	LOGICAL VALUE HELD BY THE FLIP-FLOP 130-2	LOGICAL VALUE OBTAINED AT THE OUTPUT OF THE EXCLUSIVE-OR GATE 131	LOGICAL VALUE HELD BY THE FLIP-FLOP 130-3
--	--	--	--	--	12
d1	120d1	10	11	120d1011	110120d1
d2	110120d10d2	120d1	10	110120d10d2010	100110120d10d2
d3	100110120d10d20d3	100110120d10d20d3	120d1	100110120d10d20d30120d1	100110d20d3
d4	100110d20d30d4	100110d20d30d4	100110120d10d2	100110d20d30d40110120d10d2	100120d10d30d4
d5	100120d10d30d40d5	100120d10d30d40d5	100110d20d30d4	100120d10d30d40d5010011012	110d20d40d5
d6	110120d40d50d6	110120d40d50d6	100120d10d30d40d5	110120d40d50d60100110d20d30d4	10d30d50d6
d7	100d30d50d60d7	100d30d50d60d7	110d20d40d50d6	100d30d50d60d70100120d10d30d4	120d10d40d50d60d7
d8	--	10=	11=	d5	12=
	120d10d40d50d60d70d8	120d10d40d50d60d70d8	100d30d50d60d7	120d10d40d50d60d70d8 0110d20d40d50d6	110120d10d20d30d50d60d70d8

FIG. 6


	LOGICAL VALUE HELD BY THE FLIP-FLOP 131-1	LOGICAL VALUE HELD BY THE FLIP-FLOP 131-2	LOGICAL VALUE HELD BY THE FLIP-FLOP 131-3	LOGICAL VALUE OBTAINED AT THE OUTPUT OF THE EXCLUSIVE-OR GATE 132-1	LOGICAL VALUE OBTAINED AT THE OUTPUT OF THE EXCLUSIVE-OR GATE 132-2
--	c0	c1	c2	--	--
f1	f1	c0	c1	$g1 = c0 \oplus f1$	$g2 = c1 \oplus f1$
f2	f2	f1	c0	$g3 = f1 \oplus f2$	$g4 = c0 \oplus f2$
f3	f3	f2	f1	$g5 = f2 \oplus f3$	$g6 = f1 \oplus f3$
f4	f4	f3	f2	$g7 = f3 \oplus f4$	$g8 = f2 \oplus f4$
f5	f5	f4	f3	$g9 = f4 \oplus f5$	$g10 = f3 \oplus f5$
f6	f6	f5	f4	$g11 = f5 \oplus f6$	$g12 = f4 \oplus f6$
f7	f7	f6	f5	$g13 = f6 \oplus f7$	$g14 = f5 \oplus f7$
f8	f8	f7	f6	$g15 = f7 \oplus f8$	$g16 = f6 \oplus f8$


FIG. 7






# FIG. 8







PRIOR ART FIG. 10



# PRIOR ART FIG. 11



Under the Paperwork Reduction Act of 1995, no persons are required to respond to a collection of information unless it displays a valid OMB control number.

**Declaration and Power of Attorney For Patent Application****特許出願宣言書及び委任状****Japanese Language Declaration****日本語宣言書**

下記の氏名が発明者として、私は以下の通り宣言します。

As a below named inventor, I hereby declare that:

私の住所、私書箱、国籍は下記の私の氏名の後に記載された通りです。

My residence, post office address and citizenship are as stated next to my name.

下記の名称の発明に関して請求範囲に記載され、特許出願している発明内容について、私が最初かつ唯一の発明者（下記の氏名が一つの場合）もしくは最初かつ共同発明者である（下記の名称が複数の場合）信じています。

I believe I am the original, first and sole inventor (if only one name is listed below) or an original, first and joint inventor (if plural names are listed below) of the subject matter which is claimed and for which a patent is sought on the invention entitled

CODING ASSISTING EQUIPMENT,  
DECODING ASSISTING EQUIPMENT,  
RADIO TRANSMITTER, AND RADIO RECEIVER

上記発明の明細書（下記の欄でx印がついていない場合は、本書に添付）は、

the specification of which is attached hereto unless the following box is checked:

☐ 月 日に提出され、米国出願番号または特許協定条約国際出願番号を \_\_\_\_\_ とし、  
（該当する場合） \_\_\_\_\_ に訂正されました。☐ was filed on \_\_\_\_\_  
as United States Application Number or  
PCT International Application Number  
\_\_\_\_\_ and was amended on  
\_\_\_\_\_ (if applicable).

私は、特許請求範囲を含む上記訂正後の明細書を検討し、内容を理解していることをここに表明します。

I hereby state that I have reviewed and understand the contents of the above identified specification, including the claims, as amended by any amendment referred to above.

私は、連邦規則法典第37編第1条56項に定義されるとおり、特許資格の有無について重要な情報を開示する義務があることを認めます。

I acknowledge the duty to disclose information which is material to patentability as defined in Title 37, Code of Federal Regulations, Section 1.56.

Under the Paperwork Reduction Act of 1995, no persons are required to respond to a collection of information unless it displays a valid OMB control number.

# Japanese Language Declaration (日本語宣言書)

私は、米国法典第35編119条(a)-(d)項又は365条(b)項に基づき下記の、米国以外の国の少なくとも一カ国を指定している特許協力条約365(a)項に基づく国際出願、又は外国での特許出願もしくは発明者証の出願についての外国優先権をここに主張するとともに、優先権を主張している、本出願の前に出願された特許または発明者証の外国出願を以下に、枠内をマークすることで、示しています。

## Prior Foreign Application(s)

外国での先行出願

Hei 11-215290

(Number)  
(番号)

JAPAN

(Country)  
(国名)

I hereby claim foreign priority under Title 35, United States Code, Section 119(a)-(d) or 365(b) of any foreign application(s) for patent or inventor's certificate, or 365(a) of any PCT International application which designated at least one country other than the United States, listed below and have also identified below, by checking the box, any foreign application for patent or inventor's certificate, or PCT International application having a filing date before that of the application on which priority is claimed.

Priority Not Claimed

優先権主張なし

29/07/1999

(Day/Month/Year Filed)  
(出願年月日)

☐

(Number)  
(番号)

(Country)  
(国名)

(Day/Month/Year Filed)  
(出願年月日)

☐

私は、第35編米国法典119条(e)項に基づいて下記の米国外特許出願規定に記載された権利をここに主張いたします。

(Application No.)  
(出願番号)

(Filing Date)  
(出願日)

(Application No.)  
(出願番号)

(Filing Date)  
(出願日)

私は、下記の米国法典第35編120条に基づいて下記の米国外特許出願に記載された権利、又は米国を指定している特許協力条約365条(c)に基づき権利をここに主張します。また、本出願の各請求範囲の内容が米国法典第35編112条第1項又は特許協力条約で規定された方法で先行する米国外特許出願に開示されていない限り、その先行米国外特許出願提出日以降で本出願書の日本国内または特許協力条約国際提出日までの期間中に入手された、選利規則法典第37編1条56項で定義された特許資格の有無に関する重要な情報について開示義務があることを認識しています。

(Application No.)  
(出願番号)

(Filing Date)  
(出願日)

(Status: Patented, Pending, Abandoned)  
(状況: 特許許可済、係属中、放棄済)

(Application No.)  
(出願番号)

(Filing Date)  
(出願日)

(Status: Patented, Pending, Abandoned)  
(状況: 特許許可済、係属中、放棄済)

私は、私自身の知識に基づいて本宣言書中で私が行なう表明が真実であり、かつ私の入手した情報と私の信じていることに基づき表明が全て真実であると信じていること、さらに故意になされた虚偽の表明及びそれと同等の行為は米国法典第18編第1011条に基づき、罰金または拘禁、もしくはその両方により処罰されること、そしてそのような故意による虚偽の表明を行なえば、出願した、又は既に許可された特許の有効性が失われることを認識し、よってここに上記のごとく宣誓を致します。

I hereby declare that all statements made herein of my own knowledge are true and that all statements made on information and belief are believed to be true; and further that these statements were made with the knowledge that willful false statements and the like so made are punishable by fine or imprisonment, or both, under Section 1001 of Title 18 of the United States Code and that such willful false statements may jeopardize the validity of the application or any patent issued thereon.

Under the Paperwork Reduction Act of 1995, no persons are required to respond to a collection of information unless it displays a valid OMB control number.

# Japanese Language Declaration (日本語宣言書)

委任状: 私は下記の発明者として、本出願に関する一切の  
手続きを米特許商標局に対して遂行する弁護士または代理人  
として、下記の者を指名いたします。(弁護士、または代理  
人の氏名及び登録番号を明記のこと)

POWER OF ATTORNEY: As a named inventor, I hereby appoint  
the following attorney(s) and/or agent(s) to prosecute this  
application and transact all business in the Patent and Trademark  
Office connected therewith (list name and registration number)

書類送付先

Aaron B. KARAS, Reg. No. 18,923; Samson HELFGOTT,  
Reg. No. 23,072 and Leonard COOPER Reg. No. 27,625  
Send Correspondence to:  
HELFGOTT & KARAS, P.C.  
Empire State Building, 60th Floor  
New York, New York 10118  
United States of America

直接電話連絡先: (名前及び電話番号)

Direct Telephone Calls to: (name and telephone number)

Helgott & Karas, P.C.  
(212) 643-5000

唯一または第一発明者名	Full name of sole or first inventor
発明者の署名	Inventor's signature
日付	Date
住所	Residence
国籍	Citizenship
私書箱 c/o FUJITSU LIMITED	Post Office Address
1-1, Kamikodanaka 4-chome, Nakahara-ku, Kawasaki-shi, Kanagawa	211-8588 Japan
第二共同発明者	Full name of second joint inventor, if any
第二共同発明者	Second inventor's signature
日付	Date
住所	Residence
国籍	Citizenship
私書箱	Post Office Address

(第三以降の共同発明者についても同様に記載し、署名を  
すること)

(Supply similar information and signature for third and subsequent  
joint inventors.)

THE UNITED STATES PATENT AND TRADEMARK OFFICE

In re the Application of: **Masatsugu FUJII**

Filed: : **Concurrently herewith**

For : **CODING ASSISTING EQUIPMENT, DECODING ASSISTING  
EQUIPMENT, RADIO TRANSMITTER, AND RADIO RECEIVER**

Serial No.: **Concurrently herewith**

March 29, 2000


Assistant Commissioner of Patents  
Washington, D.C. 20231

**SUB-POWER OF ATTORNEY**

S I R:

I, Samson Helfgott, Reg. No. 23,072 attorney of record  
herein, do hereby grant a sub-power of attorney to Linda S.  
Chan, Reg. No. 42,400, Jacqueline M. Steady, Reg. No., 44,354  
and Harris A. Wolin, Reg. No. 39,432 to act and sign in my  
behalf in the above-referenced application.

Respectfully submitted,

  
\_\_\_\_\_  
Samson Helfgott  
Reg.No 23,072

HELFGOTT & KARAS, P.C.  
60th FLOOR  
EMPIRE STATE BUILDING  
NEW YORK, NY 10118  
DOCKET NO.: FUJX17.182  
LHH:power

Filed Via Express Mail  
Rec. No.: EL522391580US  
On: March 29, 2000  
By: Lydia Gonzalez  
Any fee due as a result of this paper,  
not covered by an enclosed check may be  
charged on Deposit Acct. No. 08-1634.